



Audience AR802

In this documentation you will find information about:

- Description
- Key features
- Technical specifications

Description

The AR802 Amplifier rack is specially designed for use with SA Line Array enclosures AV27 and AB37 elements.

Key features

- Fully integrated power system
- Extreme high power to size ratio
- Superior signal reproduction
- First class connectors and cabling

Technical specifications

Electrical

Signal processing	:	presets for various controllers are available on request, or four dedicated EFN prints in the ES40 amps
Power consumption	:	400VA standby, 5600VA 1/8 max. output power pink noise
Electrical connections	:	3p+N+A 16Amp CEE form

Cabling

Mains	:	depending on your country
Speakers	:	8-conductor wires with SpeakON NL8 for AV27, 4-conductor wires for the AB37 with SpeakON NL4

Mechanical

Rack construction	:	Birch plywood, Perstorp finish, 4 handles
Physical dimensions (H x W x D)	:	690mm x 715mm x 595mm (27.2" x 28.1" x 23.4")
Weight	:	90kg (198.4lb)
Warranty	:	5 years limited (1 year on 'moving parts')